

Rua Doutor Jesuíno Maciel, 1740 Campo Belo  
São Paulo - SP - CEP 04615-005

Fone: + 55 11 5535-0050  
www.flexmedia.com.br

## Conversor Ethernet 10/100 TX/RX – 2 Fibras – Multimodo – 2km com fonte Interna 12 a 48VDC



Código	Descrição
<b>MCFO/ETHM 2F ST</b>	10/100 TX/RX 2 FO – MM – 2km – ST Fonte Interna 12 a 48VDC

<b>Port</b>	One port 10/100Base-TX RJ45 connector (Data) One port 100M Fiber Port SC/ST
<b>Protocol</b>	IEEE802.3 IEEE802.3i 10BASE-T IEEE802.3u100BASE-TX IEEE802.3x IEEE 802.3z 100BASE-X
<b>Ethernet port feature</b>	10/100BaseT (X) auto, full/half MDI/MDI-X auto
<b>Working mode</b>	Store and Forward (Full speed)
<b>Bandwidth</b>	1Gbps
<b>Data Forwarding Rate</b>	0.72Mpps
<b>MAC</b>	1K
<b>Data Buffer</b>	768K
<b>Distance</b>	10BASE-T : Cat3,4,5 UTP(≤250 meter) 100BASE-TX : Cat5 or later UTP(150 meter) Fiber up to 160KM
<b>Stand-by Power</b>	≤2W;
<b>LED Indicator</b>	POWER: Port: Ethernet link indicator: Green/10M+Yellow/100M Uplink3: Fiber port link indicator 24VDC STLZ power connector
<b>Working Tem./Humidity</b>	-10~+55°C; 5%~90% RH
<b>Store Tem./Humidity</b>	-40~+75°C; 5%~95% RH
<b>Product Size (L*W*H)</b>	Internal power supply: 140*110*30mm
<b>Install</b>	Desktop, Support DIN
<b>Protection</b>	Lighting Protection: 3KV 8/20us; Waterproof: IP30